

WPS-1 and Simple Booth Photo Booth Software Connection Guide

Simple Booth has integrated the WPS-1 as a printing output option as well as social media sharing. This document outlines how to connect the two to send prints automatically or users can press a button for multiple copies.

NOTE: The Simple Booth app works for the iPad only.

1. Prepare devices:

- a. Turn printer(s) on and load media. The power LED should be green.
- b. Plug the printer USB cable(s) into WPS-1. For 1 printer, use USB-1 port.

NOTE: Simple Booth is optimized for use with one printer.

- c. Power up WPS-1, wait for Power-on Self-test sample, POST, print to verify print server is functioning. The WPS version 1.1 firmware takes about 2 minutes to complete POST.
- d. Power-up the iPad. (Visit www.simplebooth.com for compatibility models).
- e. Download the Simple Booth app. (Email to info@simplebooth.com to obtain compatible version).

2. Connect and make test print.

- a. On the iPad mobile device, connect to WPS SSID (e.g., WPSxxxx).
- b. On the iPad, launch the Simple Booth app and login. (Visit www.simplebooth.com for details on creating an account.) Click **Open** to access settings panel.
- c. From the Simple Booth app, scroll to the **Send Options** box and ensure that either (or both) the **Print Button** and **Auto Print** are enabled.
- d. Scroll to the **Prints** settings box and verify that **WPS-1 is detected** is displayed under **Printer Setup**.

NOTE: Simple Booth's default print gateway is AirPrint. WPS does not support AirPrint.

- e. Click **Test Print** located in the right corner of the **Prints** box to verify app can print to WPS.
- f. User can make additional configuration changes to their photo booth strips.
- g. Click the arrow in the upper right corner to launch the app.

3. Launch the photo booth software, take pictures and make prints.

- a. After clicking through the set-up screen, the app will display, **Entering Booth Mode**, click **OK**.
- b. Adjust exposure and tap through to start automated photo booth application. Simple Booth will automatically take pictures and make a print. User can reprint or send files if desired.

Note:

To use web-based social media/email features, WPS must be connected to an active internet connection via an Ethernet cable.

Contact DNP IAM Technical Support

If you are still experiencing issues, contact DNP IAM using one of the following methods:

Phone: 1-855-367-7604

Email: dnp.support@dnp.imgcomm.com

Weekday Hours: Monday-Friday 9am EST – 6pm EST

Weekend Hours: Saturday and Sunday Closed